

Actiontec® GT701

How to Configure a Basic Dynamic or Single Static IP Setup

Internet Service Provider (ISP):
Qwest® with Windows Live, MSN® Premium, Qwest.net® or
Office Plus (also known as qwestoffice.net)



Use this document if:

- You need to configure your Actiontec GT701.

This document assumes:

- You need to configure your modem with a **dynamic** IP address or a **single** static IP address.
- Your modem is connected directly to your computer.

1. Open your Web browser. In the location or address bar, type 192.168.0.1.

Address	192.168.0.1
---------	-------------

2. Select **Quick Setup**.



3. Select **Next**.

Welcome to the Quick Setup

Before you begin, please make sure you have completed the following steps.

1. The Green Phone Cable is firmly plugged into your Phone Jack and into the Green Port on the High Speed Internet DSL Modem.
2. Please make sure that you have your Welcome Letter (ISP Worksheet) handy that was provided by your ISP.

Click **NEXT** to continue.

4. Select **No**. Select **Next**.

Are you an MSN user? Yes No

Once you have made your selection, click **NEXT** to continue.

5. Select **PPPoE**.

Select the item below that is utilized by your ISP.

- PPPoA**
- PPPoE**
- RFC 1483 Transparent Bridging**
- RFC 1483 via DHCP**
- RFC 1483 via Static IP**

6. Enter your **Username** and **Password**.

Enter your PPP User Name and Password. (PPPoA and PPPoE ONLY)

PPP User Name

PPP Password

7. Select **Apply**.

Now click **Apply** below to save your changes.

8. This will reboot the router with the new settings. When the power LED light stops flashing, you can try to connect to the internet.

Thankyou

Please wait while we apply the changed settings to the modem. When modem changes are applied successfully, you will be taken back to the page apply was selected on.